

## How to Setup ICA/LPD Printing for the 1000 Series

This test was preformed using Windows 2000 SP4 / MX FR3 on the server and Firmware Version 4.2.137 and 4.3.033 on the 1000 series.

1. Install print drivers on ICA server and locate the print driver name.
2. Physically connect the printer to the 1000 series terminal.
3. On the terminal go to **DESKTOP / SYSTEM SETTINGS / PRINTER**.
4. Under **PRINTER SETUP / local** you will need to fill in the fields with the appropriate information.
  - a. Select Port – Specify correct port the printer is attached to.
  - b. Printer Name – Give the printer a name.
  - c. Printer Identification – Specify the correct print driver name.

**\* When you specify the print driver name be sure to enter the name exactly as it specified on the server. Pay close attention to Capital letters and spaces.**
5. Check **“Enable the Printer device”** and **“Enable LPD service for the printer”**.
6. Now click test print and make sure the terminal can print to the local printer.
7. Attach to ICA session and verify the printer shows under **START / CONTROL PANEL / PRINTERS**.
8. Connect 2<sup>nd</sup> 1000 series terminal to an ICA session on the same ICA server and verify under **START / CONTROL PANEL / PRINTERS** the auto-created printer in listed. You can now perform a test print if you would like.